



Hardware Acceleration of Adaptive Neural Algorithms

Hardware Acceleration of Adaptive Neural Algorithms



Designing an Analog Crossbar based Neuromorphic Accelerator

Sapan Agarwal, Alexander Hsia, Robin Jacobs-Gedrim, David R. Hughart,
Steven J. Plimpton, Conrad D. James, Matthew J. Marinella
Sandia National Laboratories




Sandia National Laboratories is a multimission laboratory managed and operated by National Technology and Engineering Solutions of Sandia, LLC, a wholly owned subsidiary of Honeywell International, Inc., for the U.S. Department of Energy's National Nuclear Security Administration under contract DE-NA0003525.

The Von Neumann Bottleneck



Current Transistors ~ 10 aJ
40kT Noise Limit ~ 0.2 aJ

Cross chip communications ~ 1 pJ
DRAM Access >10 pJ
Ethernet ~ 1 nJ



Processor Layer

Photonic Layer

Optical interconnects 100 fJ to 1 pJ

**Communications require
orders of magnitude more
energy!**

Use Resistive Memories for Local Computation




$$V = I \times R$$



$$I = G \times V$$

multiplication


- A resistive memory or ReRAM is a programmable resistor
 - Apply small voltages allows the conductance to be read: $I = G \times V$
 - Apply large voltages to change the resistance



$$\text{Addition: } I = I_1 + I_2$$





Directly Process in the Memory Itself



Analog is efficiently and naturally able to combine computation and data access

Effectively, large-scale processing in memory with a multiplier and adder at each real-valued memory location


Crossbars Can Perform Parallel Reads and Writes



Energy to charge the crossbar is CV^2
 $E \propto C \propto \text{number of RRAMs} \propto N \times M$

$$E \sim O(N \times M)$$

SRAM Arrays Require Charging Columns Multiple Times



SRAMs must be read one row at a time, charging M columns
Each column wire length is $O(N)$.


Energy = N Rows $\times$ M Columns $\times$ $O(N)$ wire length

Energy $\sim O(N^2 \times M)$


$O(N)$ times worse than a crossbar!

Want To Accelerate Many Different Neural Algorithms


Backpropagation





Sparse Coding



Liquid State Machine



Crossbars Can Perform Parallel Reads and Writes





Energy to charge the crossbar is CV^2
 $E \propto C \propto \text{number of RRAMs} \propto N \times M$

$$E \sim O(N \times M)$$

General Purpose Neural Architecture

Run *any* neural algorithm on the same hardware





Neuromorphic core:

- Evaluate vector matrix multiplies along rows or columns
- Train based on input vectors


Digital Core:

- Process neural core inputs/outputs
- For NxN crossbar, the crossbar accelerates $O(N^2)$ operations leaving only $O(N)$ operations for the digital core

Can Run Neural Networks on this Architecture




Back Propagation




Design & Model Detailed Architecture


Vector Matrix Multiply




Matrix Vector Multiply




Outer product Update




Neuron Circuitry



Current Conveyor Based Integrator




Comparator




Row & Column Driver Circuitry


Row Driver Logic




Voltage level shifter (drive high V transistor with low V)



Column Driver Logic




Array driver pass transistors



Compare Architectures

1024 x 1024 = 1M array operations, sum over 1 training cycle, 3 operations:

- Vector Matrix Multiply
- Matrix Vector Multiply
- Outer Product Update




Used a commercial 14/16 nm PDK

***Requires 100 M Ω on state devices


Neural Core Energy Analysis

Analog ReRAM



8 bits In/out
8 bit weights







4 bits In/out
8 bit weights







2 bits In/out
8 bit weights





Digital ReRAM



SRAM




Multiscale Model of a Neural Training Accelerator




CROSS SIM

Sandia Cross-Sim:

Translates device measurements and crossbar circuits to algorithm-level performance



Memristor fabrication and measurements in MESAFab



DFT of model of oxide physics, bands

Materials


In situ TEM of filament switching: Use DFT model to interpret EELS signature

Target Algorithms

- Deep Learning
- Sparse Coding
- Liquid State Machines


Algorithms

Architecture




Modified McPAT/CACTI: Model performance and energy requirements

Circuits







Sandia's Xyce Circuit Sim: Simulate crossbar circuits based on our devices

Devices




Drift-diffusion model of ReRAM band diagram & transport (REOS, Charon)




#ROSS SIM


<https://cross-sim.sandia.gov>




The screenshot shows the CrossSim website interface. At the top, there's a navigation bar with the Sandia National Laboratories logo and links for Locations, Contact Us, and Employee Locator. Below this is the 'Crossbar Simulator' header with the #ROSS SIM logo. The 'About CrossSim' section describes the simulator's purpose in modeling resistive memory crossbars for neuromorphic computing. It mentions a clean Python API and the ability to model realistic device properties and variability. A diagram illustrates a 4x4 crossbar array with input voltages $V_1=x_1, V_2=x_2, V_3=x_3, V_4=x_4$ and weights w_{ij} in the intersections. The 'Download' section provides links for the user manual, the simulator code, and example scripts. The 'Contact Us' section provides an email address for Sapan Agarwal. The 'Selected Publications Using CrossSim' section lists several papers, including one from the 2017 IEEE Symposium on VLSI Technology.



Measured
Devices



Algorithmic
Performance



Simple Python API:

Do a matrix vector multiplication

`result = neural_core.run_xbar_mvm(vector)`

Simple API to model crossbars

```
# ***** set parameters defining the crossbar

params.algorithm_params.weights.sim_type = "XYCE" # Use a XYCE based sim
params.algorithm_params.weights.maximum = 10 # clipping limits
params.algorithm_params.weights.minimum = -10 # clipping limits
params.xyce_parameters.xbar.device.TAHA_A1 = 4e-4 # Xyce Parameters
...
...


# ***** API for running neural operations
# All crossbar details are transparent to the user

# Create a neural_core object that models a crossbar
neural_core = MakeCore(params=params)


neural_core.set_matrix(weights) # set the initial weights
result = neural_core.run_xbar_vmm(vector) # Do a vector matrix multiply
result = neural_core.run_xbar_mvm(vector) # Do the transpose, a matrix vector mult.
neural_core.update_matrix(vector1,vector2) # Do an outer product update
```

Go from Measurement to Accuracy


Fabricate Device





Measured Pulsing



ΔG Scatterplot




Cumulative Probability of ΔG




Multi-ReRAM Synapse: Periodic Carry

If we need more bits per synapse, use multiple memristors



- Three 10 level ReRAMs could represent 1-1000!
- Adding to the weight requires reading every ReRAM to account for any carries and serially programming each ReRAM: VERY EXPENSIVE



- Use >10 levels to represent a base 10 system
- Ignore carry and program the crossbar in parallel.
- Periodically (once every few hundred cycles) read the ReRAM and perform the carry



Periodic Carry Compensates for Write Noise



- Read and reset every 100 pulses
Do 300,000 small (0.02% of weight range) updates
- net of 1500 positive training pulses


Noise Sigma = 1.4% for single device

- (from $\sigma_{noise}/G_{range} = 0.1\sqrt{\Delta G/G_{range}}$)
- Write noise applied during updates and carries


Learn from a 0.5% Signal

Periodic Carry Mitigates Write Nonlinearity



Write Nonlinearity



Alternating Pulses Cause Weight Decay






Use center linear range of weights



- Train with 1% signal
- Ideal result is 0.6





TaO_x Results



A/D and D/A is modeled, Serial operations modeled

- When resetting weight, need to adjust pulse size based on current state to compensate for nonlinearity
- When reading a single weight, need to adjust readout range to be smaller (change capacitor on the integrator)


Li-Ion Synaptic Transistor for Analog Computation (LISTA)



Off by $\sim 1\%$
from Ideal

E. J. Fuller, et al, "Li-Ion Synaptic Transistor for Low Power Analog Computing," *Advanced Materials*, vol. 29, no. 4, p. 1604310, 2017.

Summary





- Fundamental $O(N)$ energy scaling advantage
- Use CrossSim to co-design materials to algorithms
 - Use periodic carry to overcome noise devices
- Need high resistance 10-100 M Ω Devices
- Need low write nonlinearities

CROSS SIM


<https://cross-sim.sandia.gov>

Extra Slides

Overcoming the Power Limit






Richard Goering, "Three Die Stack -- A Big Step "Up" for 3D-ICs with TSVs" Cadence blog



Integrate Processing and Memory

The Noise Limited Energy to Read a Crossbar Column is Independent of Crossbar Size



Measure N resistors and determine the total output current with some signal to noise ratio (SNR)*

What is the minimum energy?

$$Energy = \underbrace{V^2 G_o \times N}_{\text{Power in each resistor} \times \text{number of resistors}} \times \frac{1}{\Delta f} \leftarrow \text{Determined by noise and SNR}$$

Power in each resistor ×
number of resistors

Determined by
noise and SNR

If we double the number of resistors, we can double the speed to get the same energy and SNR.

This is because the noise scales as sqrt(N) while the signal scales as N

$$Energy = 4k_b T \times SNR^2$$

$$\text{Thermal Noise} = \langle \Delta I^2 \rangle$$

$$= N \times (4k_b T \times G_o \times \Delta f)$$

$$SNR^2 = \frac{(NI_o)^2}{\langle \Delta I^2 \rangle}$$

$$\frac{1}{\Delta f} = 4k_b T \times SNR^2 \times \frac{1}{V^2 G_o \times N}$$


*we are assuming we need some fixed precision on the output, and don't need full floating point accuracy

Experimental Device Non-idealities


Device: **Write Variability, Write Nonlinearity, Asymmetry, Read Noise**

Circuit: A/D, D/A noise, parasitics



Variability and Nonlinearity



Read Noise




Full System Simulation




	Range	Bits
Row Input	-1 to 1	8
Col Output	-6 to 6	8
Col Input	-1 to 1	8
Row Output	-4 to 4	8
Row Update	-0.01 to 0.01	7
Col Update	-1 to 1	5

A/D & D/A Have Minimal Impact






Data set	#Training/Test Examples	Network Size
File Types	4,501 / 900	256×512×9
MNIST	60,000 / 10,000	784×300×10

TaO_x Results





Carry once every 1000 updates for the LSB, and every 2 updates on others



A/D and D/A is modeled, serial operations modeled

- When resetting weight, need to adjust pulse size based on current state to compensate for nonlinearity
- When reading a single weight, need to adjust readout range to be smaller (change capacitor on the integrator)


LISTA Results



- Carry once every 1000 updates
- Use a single device per weight and subtract a reference current


Neural Core Latency Analysis

Analog ReRAM




Digital ReRAM

All bit precisions




SRAM

All bit precisions



Neural Core Area Analysis



For the ReRAM, high voltage transistors require 8X area, improving this could give ~2X area savings